

## LED 200W COB PAR LIGHT ( W+Y)



USER MANUAL

## 1. Installation requirement

1. Please choose the suitable place put or hang the light when installing. You must use the appreciative hook and screws when hanging the light, and make sure the weight of the light is suit for the hanger.
2. Make sure there is no flammable substances within 0.5m when installing the light.
3. Please ask the professional person install the light, any wrongful installation will lead the body injury and material damage.

## 2. Technical Parameters:

Voltage: 110v-240v, 50Hz-60Hz

Lamp source: 200W COB


Color: Warm white + Cool Yellow

Signal control: 2 / 4 / 6 CH

Operational Mode: DMX512, Master-slave, Auto-run, Sound control.

N. W: 3.5KGS

## 3. Button Instruction



- A. Menu button :Set up and selection
- B. UP button:Add Value
- C. Down button:Reduce Value
- D. Enter button: Confirm
- E. LED display

Operating instructions: Press Button A to choose 9 different functions. The first two digits represent function you choose .(Refer to the function table).The last two digits represent the address code or speed parameter of this function.Press the B or C button to change value.Press D button to confirm.

## 4. Menu Instruction

LED Display function comparison table, (all functions can be selected by pressing the D button to confirm)

No.	Display	Function	Value	
1	A001	DMX address	001-512	Press B, C buttons to change value
2	2CH-4CH-6CH		Channel choose	
3	CC 99	Colorful fade	01-99	Press B, C buttons to change the fade speed
4	CP 99	Colorful Gradient	01-99	Press B, C buttons to to change the gradient speed
5	DE99	Colorful Pulse	01-99	Press B, C buttons to change the combination speed
6	BEBE	Sounds control		
7	Y220	Yellow color	001-255	Press B, C buttons to change the color
8	W220	White color	001-255	Press B, C buttons to change the color
9	ON / OFF		Display screen saver ON/OFF	

LED background display window function comparison table, (in A001 mode, press the function button for 10 seconds to enter the background to modify parameters, and press the button to confirm to save and exit).

No.	Display	Manual	
1	W235	White color current 20-255	Press B or C button to change values
2	Y235	Yellow color current 20-255	Press B or C button to change values
3	E150	The console adjusts the dimming speed 0-255	Press B or C button to change values
4	C-60	The temperature control	Temperature is set at 40-70 degrees Press B or C button to change values

## 5. DMX512 Channel Manual (A6ch)

CH	Function	Description	
CH 1	Dimmer	Dimmer,linear dimming	The brightness from dark to bright
CH 2	Strobe	Strobe	From slow to fast

CH 3	Function	0--50	DMX Channel control
		51--100	Fade
		101--150	Gradient
		151--200	Pulse variable
		201--255	Sound control
CH 4	Speed	From slow to fast	
CH 5	Y Dimmer	Y dimmer ,linear dimming,from dark to bright	
CH 6	W Dimmer	W dimmer,linear dimming,from dark to bright	

### DMX512 Channel Manual(B6ch)

CH	Function	Description	
CH 1	Dimmer	Dimmer,linear dimming	The brightness from dark to bright
CH 2	Y Dimmer	Y dimmer ,linear dimming,from dark to bright	
CH 3	W Dimmer	W dimmer ,linear dimming,from dark to bright	
CH 4	Strobe	Strobe	From slow to fast
CH 5	Function	0--50	DMX Channel control
		51--100	Fade
		101--150	Gradient
		151--200	Pulse variable
		201--255	Sound control
CH 6	Speed	From slow to fast	

### 6. DMX512 Channel Manual(A4ch)

CH	Function	Description
CH 1	Dimmer	Dimmer ,linear dimming,from dark to bright
CH 2	Y Dimmer	Y dimmer ,linear dimming,from dark to bright
CH 3	W Dimmer	W dimmer ,linear dimming,from dark to bright
CH 4	Strobe	Strobe, from slow to fast

### DMX512 Channel Manual(B4ch)

CH	Function	Description	
CH 1	Dimmer	Dimmer ,linear dimming,from dark to bright	
CH 2	Strobe	Strobe, from slow to fast	
CH 3	Function	0--50	DMX Channel control
		51--100	Fade
		101--150	Gradient
		151--200	Pulse variable
		201--255	Sound control
CH 4	Speed	From slow to fast	

### 8. DMX512 Channel Manual(A2ch)

CH	Function	Description
CH 1	Dimmer	Dimmer ,linear dimming,from dark to bright
CH 2	Strobe	Strobe, from slow to fast

### 9.DMX512 Channel Manual(B2ch)

CH	Function	Description
CH 1	Y Dimmer	Y dimmer ,linear dimming,from dark to bright
CH 2	W Dimmer	W dimmer ,linear dimming,from dark to bright

### 10. Function Features:

Operation is very simple, user-friendly design, dimming no flicker, jitter phenomenon.Can be adapted to photography, television and other places with strict requirements on lighting.